

## Key 177 NP BTE

4-channel Normal/High Power BTE with fitting range 20–100 dB. NP BTE receiver option. Compatible with iPhone and Android (ASHA) and supports ReSound Assist Live. Streaming (MFI & ASHA) available only in Key 3 & Key 4 models.

### Features

- RESOUND KEY NORMAL & HIGH POWER BTE
- Made for iPhone + made for Android with ASHA + Resound Assist Live (MFI & ASHA streaming only in Key 3 & 4)
- NO OF CHANNELS: 4
- RECEIVER OPTIONS: NP BTE
- FITTING RANGE: 20–100



### ADDRESS

99, Princess Street, Sancheti  
Bhavan, Opp. Earth Baug Bldg,  
Mumbai 400 002

### CONTACT

onymed33@gmail.com  
+91 97690 31545